

Start | QUEUES | Data Folders | Archive | Setup Submit | Associated Files | Other Add-ons | Version Upgrade

Queue Setup	Print to ANY Windows Printer	🔂 PDF version					
What is a Queue							
Create a Queue	Overview						
Queue Properties	This facility is only available for PCLXL (PCL6) files where the	"Print to ANY Windows Printer" chargeable option is included in their					
Print to ANY Windows Printer	Formrap system. Files must be generated through a queue v	Vitra Data File showing the PCLXL (PCL6) symbol.					
Tools	To print to other Windows printers, use a filter for each differe	nt printer you want to print to.					
	The table shows relative file sizes from which the demands of by a factor of 20 - 30 over the equivalent direct outputs, althout	the process, especially for PostScript, is shown. Converted files are larger ugh the PDF file produced from PostScript is still small and efficient.					
	A four page "Accounts Report" formatted with FormTrap in Ar as the text file. The form file and data files may be downloade	ial True Type font, compressed down from a seven page original was used d from here:					
	Download of PCLXL-to-Any-Windows.zip						
	Printer used is an HP Color LaserJet 4600 printed in B&W wit	h no logos:					
	Print Language	File size - Bytes					
	Original Text File	34.025					
	PCI 5	172 761					
		005 700					
	PCLXL (PCL6)	305,708					
	PostScript	351,542					
	PDF from PostScript	74,128					
	Converted via printer drivers from the original PCLXL (PCL6)	file via filter:					
	Original PCLXL (PCL6)	305,708					
	to PCL	5.599.651					
	to PostScrint	10 074 461					
	to PDE from DestOprint from DOL VI	10,074,401					
		142,213					
	to PCLXL	632,033					
		Top					
	Setup Filters are required to print to other windows printers from PCLXL (PCL6). Please set up individual filters for each printer you wish to						
	use. PostScript output can also be set up this way (at around	30 times the size, with corresponding processing time).					
	 Open the Filters tab and select the PCLXL to Printer filter as a model. 						

1 of 3

🕅 . 😕	Licensed to: Cate	Equipment, Inc., 50 printers	
Queues Data rolde			
💦 Lore components	Available filters:	Properties of PCLXL to any printer	-
Z Settings	Add name-value pair Arabic As4006iber	Name: PCLXL to any printer	
🚏 Filters	Cate Statement Repaginate as F	Description:	
Data input	Delivery selection	Converts PCLXL into "Printername"'s	
File system	PCL to TIFF PCL XL to any printer	To use, go to Setup, Filters and replace	
P (Line printer) Named pipes	PCLXL to Canon iP100 on P		
Delivery	PCLXL to TIFF PostScript to PDF	<u></u>	
Print servers	PostScript to TIFF Preliminary Cheque Filter	Path: pclxlprn.exe	
E-mail	Remove PCL5 escapes Replace data name	Arguments:	
Applications	Western	-pPrintername -o-	
		a nual directory,	
		Input type: pclxl	
		Use standard input/output	
		Hide console (will fail for GUI application)	
		Hide GUI window (will fail for console)	
	1 / 2 / 2 / 2 / 2 / 2 / 2 / 2 / 2 / 2 /		
 2. Go to Start, Printers and Fax the name. Printers and Faxes File Edit View Favorites Tools Back Start Start	New Delete	and go to Properties . Select the printer name a	is shown and
2. Go to Start, Printers and Fax the name. Printers and Faxes File Edit View Favorites Tools Back Definition of the second Address Printer Tasks Printer Tasks Address Printer Tasks See what See what Set printer See Also So to mar	New Delete Xes, select the required printer a Help arch Polders Canon P100 serie: on plato Properties Ports Advanced Color Managemen IP100 serie Cut Cut Cut Cut Cut Cut Select All	and go to Properties. Select the printer name a Documents Status Documents Status Ready	s shown and Comments Laser Jel et 4100 l
2. Go to Start, Printers and Fax the name. Printers and Faxes File Edit View Favorites Tools Back Delta Difference Printer Tasks Add a printers and Faxes Printer Tasks Canon iP100 se See what See what See what See this See this See this Set printer See Also General Sharing Pause printer Set printer See Also Go to mar Go to mar Color: Yes	New Delete	and go to Properties. Select the printer name a Documents Status 0 Ready	S shown and Comments LaserJel et 4100 l
2. Go to Start, Printers and Fax the name.	New Delete xes, select the required printer a Help arch Folders Image: Construction of the series on plate Ports Advanced Color Management Image: Construction of the series on plate Ports Advanced Color Management Image: Construction of the series on plate Pasters Delete Image: Select All Paper available: s	and go to Properties. Select the printer name a Documents Status 0 Ready	s shown and Comments
2. Go to Start, Printers and Fax the name. Printers and Faxes File Edit View Favorites Tools Back Printers and Faxes Printer Tasks Add a printers and Faxes Printer Tasks Add a printer Canon iP100 se See what Select printer See what Select printer Canon iP100 se See what Select printer Canon iP100 se See what See trinter See Also General Sharing Pause printer See Also General Sharing Features Color: Yes Double-sided: Yes Do	New Delete xes, select the required printer a Help arch Polders Polders Canon IP100 serie Conon IP100 serie Color Management IP100 serie Color Management Pasters Delete IP100 serie Select All	and go to Properties. Select the printer name a Documents Status 0 Ready t Security Maintenance	s shown and Comments LaserJel et 4100 l
2. Go to Start, Printers and Fax the name. Printers and Faxes File Edit View Favorites Tools Back Printers and Faxes Printer Tasks Printer Tasks Printer Tasks Printer Tasks Printer Tasks Printer Tasks Canon iP100 st General Sharing Preference Pause print Set printer Set printer Set printer Set printer Set printer Comment: Comment: Comment: Comment: Color: Yes Double-sided: Yes Double-sided: Yes Double-sided: Yes Staple: No Speed: Unknown Maximum resch bit	New Delete Xes, select the required printer a Help arch Folders Folders Canon IP100 serie: on plato Properties Ports Advanced Color Managemen FP100 serie Cut Cut Cut Cut Cop Pastes Delete FP100 serie Select All For Unknown	and go to Properties. Select the printer name a Documents Status 0 Ready	s shown and Comments
2. Go to Start, Printers and Fax the name. Printers and Faxes File Edit View Favorites Tools Back Printers and Faxes Printer Tasks Address Printers and Faxes Printer Tasks Add a print Add a print Add a print See what See what See what See what See this See this Set printe See Also General Sharing Pause print See Also General Sharing Pause print See Also General Sharing Pause print See Also General Sharing Features Color: Yes Double-sided: Yes Double-side: Yes Double-sided: Yes Double-side	New Delete	and go to Properties. Select the printer name a Documents Status Documents Status Ready Total Security Maintenance Documents	Is shown and Comments LaserJel et 4100 l
2. Go to Start, Printers and Fax the name. Printers and Faxes File Edit View Favorites Tools Back Printers and Faxes Printer Tasks Printer Tasks Printer Tasks Printer Tasks Printer Tasks Canon iP100 st See what See what See this See this See this See this See this See this See this See Also General Sharing Preference See this See t	New Delete xes, select the required printer a Help arch Polders Image: Control P100 series Ports Advanced Color Management Image: Color Management Cut Ad Image: Color Management Pastex Delete iPloo serie Select All Image: Color Management Paper available: Ad Image: Color Management Printing Preferences	and go to Properties. Select the printer name a Documents Status 0 Ready t Security Maintenance t Test Page	s shown and Comments

FormTrap	Setup and Tools				
Queues 📔 Data folders	Archive	Setup		oo primero	?
Queues Data folders Archive Settings Filters Run Data input File system LP (Line printer) Named pipes Delivery Print servers Printer licensing E-mail Applications	Available filters: Add name-value pair Arabic As400filter Cate Statement Repaginate as F CR to LF Delivery selection Payment initial repaginate PCL to TIFF PCLXL to any printer PCLXL to any printer PCLXL to TIFF PCLXL to TIFF PostScript to PDF PCLXL to TIFF Preliminary Cheque Filter Remove PCLS escapes Replace data name TIFF rotate Western		Path: pctxlprn.e Arguments: -p"\\plato\Canor nitial directory: Input type:	XL to Canon iP100 on Plat Canon iP100 on Plato to "\\plato\Canon iP100 exe iP100 series" -o-	
 Replace Printer in the Name with is the final Filter: Replace Input type with pclxl ar 	New a modified version	Delete	Output type: Check status Require output Use standard Hide console (Hide GUI wind Save s (and short en te extension fro	prn ut input/output (will fail for GUI application) low (will fail for console) cough to be able to see a prn the drop down list, or	I the descriptio with prn .
6. Check these under Output type: Check status Require output Use standard input/outp Hide console Hide GUI should be Unticl	ut ked				
 Save to record this as a new filte 	er.				
ou can set up as many different filters	as there are printer	rs you want to	print to.		
o print to any Windows Printer our queue must have a PCLXL (PCL6)	Data Folder select	ed, PCLXL is r	epresented as	this symbol: Pt	
				6	

Disclaimer | Home | About Us | News Products | Customer Area | Free Trial | Success Stories | Contact Us Copyright © 1995 - 2010 TCG Information Systems Pty. Ltd. All rights reserved.